

Lecture 2: How to present the solution to a linear system

January 17, 2025

1 An Example

2 Important terminology

- Reduced row echelon form (RREF)
- Leading variables and free variables

3 Writing the solution to a system with free variables

Example: Solve the following linear system

$$\begin{array}{rclclcl} x_1 & + & 3x_2 & + & 5x_3 & - & 9x_4 & = & 5 \\ 3x_1 & - & x_2 & - & 5x_3 & + & 13x_4 & = & 5 \\ 2x_1 & - & 3x_2 & - & 8x_3 & + & 18x_4 & = & 1 \end{array}$$

$$\begin{array}{l} \left[\begin{array}{ccccc} 1 & 3 & 5 & -9 & 5 \\ 3 & -1 & -5 & 13 & 5 \\ 2 & -3 & -8 & 18 & 1 \end{array} \right] \begin{array}{l} R_2 \rightarrow R_2 - 3R_1 \\ \longrightarrow \\ R_3 \rightarrow R_3 - 2R_1 \end{array} \end{array} \quad \left[\begin{array}{ccccc} 1 & 3 & 5 & -9 & 5 \\ 0 & -10 & -20 & 40 & -10 \\ 0 & -9 & -18 & 36 & -9 \end{array} \right]$$

$$\begin{array}{l} R_2 \times \left(-\frac{1}{10}\right) \\ \longrightarrow \end{array} \quad \left[\begin{array}{ccccc} 1 & 3 & 5 & -9 & 5 \\ 0 & 1 & 2 & -4 & 1 \\ 0 & -9 & -18 & 36 & -9 \end{array} \right] \begin{array}{l} R_3 \rightarrow R_3 + 9R_2 \\ \longrightarrow \end{array} \quad \left[\begin{array}{ccccc} 1 & 3 & 5 & -9 & 5 \\ 0 & 1 & 2 & -4 & 1 \\ 0 & 0 & 0 & 0 & 0 \end{array} \right]$$

REF

$$\begin{array}{l} R_1 \rightarrow R_1 - 3R_2 \\ \longrightarrow \end{array} \quad \left[\begin{array}{ccccc} 1 & 0 & -1 & 3 & 2 \\ 0 & 1 & 2 & -4 & 1 \\ 0 & 0 & 0 & 0 & 0 \end{array} \right] \quad \text{RREF } \checkmark \quad \left(\begin{array}{l} \text{Reduced row} \\ \text{echelon form} \end{array} \right)$$

How to read the solution from the RREF

$$\left[\begin{array}{cccc|c} 1 & 0 & -1 & 3 & 2 \\ 0 & 1 & 2 & -4 & 1 \\ 0 & 0 & 0 & 0 & 0 \end{array} \right] \begin{array}{l} \text{Equation 1: } \mathbf{x_1} \\ \text{Equation 2: } \\ \text{Equation 3: } \end{array} \begin{array}{l} -x_3 + 3x_4 = 2 \\ \mathbf{x_2} + 2x_3 - 4x_4 = 1 \\ (\phantom{\mathbf{x_2}} + 0 = 0) \end{array}$$

x_1 x_2 x_3 x_4 *RHS*

- Equation 1 says $x_1 = 2 + x_3 - 3x_4$
- Equation 2 says $x_2 = 1 - 2x_3 + 4x_4$
- Equation 3 has no content (an unexpected feature of this example).

A **solution of the system** must only satisfy $x_1 = 2 + x_3 - 3x_4$ and $x_2 = 1 - 2x_3 + 4x_4$, with no restriction on the values of x_3 and x_4 .

We write s and t for the values of x_3 and x_4 in a solution of the system.

$$\text{General Solution } (x_1, x_2, x_3, x_4) = (2 + s - 3t, 1 - 2s + 4t, s, t), \quad s, t \in \mathbb{R}$$

$$(x_1, x_2, x_3, x_4) = (2 + s - 3t, 1 - 2s + 4t, s, t), \quad s, t \in \mathbb{R}$$

$$\left[\begin{array}{cccc|c} 1 & 0 & -1 & 3 & 2 \\ 0 & 1 & 2 & -4 & 1 \\ 0 & 0 & 0 & 0 & 0 \end{array} \right] \begin{array}{l} \text{Equation 1: } \mathbf{x}_1 - x_3 + 2x_4 = 2 \\ \text{Equation 2: } \mathbf{x}_2 + 2x_3 - 4x_4 = 1 \\ \text{Equation 3: } (\phantom{\mathbf{x}_1} \end{array}$$

$x_1 \quad x_2 \quad x_3 \quad x_4 \quad \text{RHS}$

The **general solution** is a concise description of **all** of the **infinitely many** solutions of the simplified system, and the original one. **Particular solutions** arise by specifying s and t in the general solution. For example

- $s = 0, t = 0$ $(x_1, x_2, x_3, x_4) = (2 + 0 - 0, 1 - 0 + 0, 0, 0) = (2, 1, 0, 0)$
- $s = 1, t = 0$ $(x_1, x_2, x_3, x_4) = (2 + 1 - 0, 1 - 2 + 0, 1, 0) = (3, -1, 1, 0)$
- $s = 5, t = 10$ $(x_1, x_2, x_3, x_4) = (2 + 5 - 30, 1 - 10 + 40, 5, 10) = (-23, 31, 5, 10)$

Exercise Check that these (and more examples that you write down) are solutions of the original system:

$$\begin{array}{rclclcl} x_1 & + & 3x_2 & + & 5x_3 & - & 9x_4 & = & 5 \\ 3x_1 & - & x_2 & - & 5x_3 & + & 13x_4 & = & 5 \\ 2x_1 & - & 3x_2 & - & 8x_3 & + & 18x_4 & = & 1 \end{array}$$

Some vocabulary and definitions

$$\begin{bmatrix} 1 & 3 & 5 & -9 & 5 \\ 3 & -1 & -5 & 13 & 5 \\ 2 & -3 & -8 & 18 & 1 \end{bmatrix} \xrightarrow[\text{Gauss-Jordan elimination}]{\text{Elementary Row Operations}} \begin{bmatrix} 1 & 0 & -1 & 3 & 2 \\ 0 & 1 & 2 & -4 & 1 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix}$$

The second matrix is in **reduced row echelon form (RREF)**. This means

- 1 Every row that is not all zeros has 1 as its first non-zero entry.
- 2 Every column that contains a **leading 1** has 0 in all other positions.
- 3 The leading 1s go left to right as we move down through the rows.
- 4 Any rows that are all zeros are at the bottom.

Remark A matrix is in **row echelon form** has the above properties *except* that leading 1's can have non-zero entries **above them** in their columns.

Example This matrix is in REF, not RREF.

Every RREF is a REF.

Not every REF is a RREF.

$$\begin{bmatrix} 1 & 2 & 3 & 0 & 4 & -2 \\ 0 & 1 & 5 & 1 & -1 & 0 \\ 0 & 0 & 0 & 0 & 1 & 20 \end{bmatrix}$$

Leading variables and free variables

$$\begin{array}{rccccrcr} x_1 & + & 3x_2 & + & 5x_3 & - & 9x_4 & = & 5 \\ 3x_1 & - & x_2 & - & 5x_3 & + & 13x_4 & = & 5 \\ 2x_1 & - & 3x_2 & - & 8x_3 & + & 18x_4 & = & 1 \end{array} \longrightarrow \left[\begin{array}{cccc|c} 1 & 0 & -1 & 3 & 2 \\ 0 & 1 & 2 & -4 & 1 \\ 0 & 0 & 0 & 0 & 0 \end{array} \right]$$

$x_1 \quad x_2 \quad x_3 \quad x_4 \quad \text{RHS}$

Leading 1s in the RREF occur in the columns of the variables x_1 and x_2 . The columns of x_3 and x_4 do not contain leading 1s.

Definition Any variables whose columns in the RREF **do not contain leading 1s** are called **free variables**. Variables whose columns **do** contain leading 1s are called **leading variables**.

In this example, x_1 and x_2 are **leading variables**, x_3 and x_4 are free.

In a solution, a free variable can take on any value.

Each non-zero row of the RREF describes how the value of **one** leading variable depends on those of the free variables.¹

¹See notes on inconsistent systems later

How to write the solution

$$\begin{array}{rccccrcr} x_1 & + & 3x_2 & + & 5x_3 & - & 9x_4 & = & 5 \\ 3x_1 & - & x_2 & - & 5x_3 & + & 13x_4 & = & 5 \\ 2x_1 & - & 3x_2 & - & 8x_3 & + & 18x_4 & = & 1 \end{array} \longrightarrow \left[\begin{array}{cccc|c} 1 & 0 & -1 & 3 & 2 \\ 0 & 1 & 2 & -4 & 1 \\ 0 & 0 & 0 & 0 & 0 \end{array} \right]$$

$x_1 \quad x_2 \quad x_3 \quad x_4 \quad RHS$

- 1 Give independent **parameter names** to the values of the free variables in a solution. Write (something like) *The values of the free variables x_3 and x_4 in a solution of the system are denoted s and t .*
- 2 Read, from the RREF, how the corresponding values of the leading variables depend on s and t . State the general solution

$$(x_1, x_2, x_3, x_4) = (2 + s - 3t, 1 - 2s + 4t, s, t), \quad s, t \in \mathbb{R}$$

Note: the last part ($s, t \in \mathbb{R}$) is an essential (not optional) part of the statement. It tells the reader what values s and t may have.

- 3 Alternative version of the statement (either form is fine):

$$(x_1, x_2, x_3, x_4) = (2, 1, 0, 0) + s(1, -2, 1, 0) + t(-3, 4, 0, 1), \quad s, t \in \mathbb{R}.$$

This version has a geometric meaning - more on that in Lecture 4.